


# BRUSHLESS MOTOR BSM32 SERIES

Output : APPROX 50W~130W  
Weight : 88g (approx)



## Application

Models and Toys

| MODEL          | VOLTAGE         |         | NO LOAD        |              | AT MAXIMUM EFFICIENCY |              |                        | STALL       |                        |              |
|----------------|-----------------|---------|----------------|--------------|-----------------------|--------------|------------------------|-------------|------------------------|--------------|
|                | OPERATING RANGE | NOMINAL | SPEED<br>r/min | CURRENT<br>A | SPEED<br>r/min        | CURRENT<br>A | TORQUE<br>g-cm<br>mN-m | OUTPUT<br>W | TORQUE<br>g-cm<br>mN-m | CURRENT<br>A |
| <b>BSM3201</b> | 7.4~11.1        | 7.4V    | 17418          | 2.30         | 76.74                 | 14.65        | 461<br>45.20           | 69.35       | 2910<br>285.3          | 64.85        |

## Specification BSM3201

